

KENWOOD

Listen to the Future

VHF/UHF FM Repeater-Base Units

TKR-750/850

High-performance features — such as 16 full-duplex channels, flash memory, and PC/manual tuning — provide crystal-clear and reliable communications to make Kenwood's TKR-750/850 VHF/UHF FM repeaters the first choice for demanding applications.

HIGH STABILITY 100% CONTINUOUS DUTY

The 50-Series high stability 1.5PPM TCXO modules, 100% duty RF power amplifier (25W output), integrated die-cast heat sink and forced-air cooling provides site-friendly, continuous operation. The TKR-750 has a high power output of 50W (at 50% duty) while the TKR-850 offers 40W (at 50% duty).

16 FULL-DUPLEX CHANNELS & SINGLE PRIORITY SCAN

With 16 full-duplex channels, these versatile repeaters can function as a base station or repeater backup unit to suit various applications. The built-in 16 channels are preset and selectable from a remote control utilizing the remote I/O connector or pre-programmed key on the front panel. The programmable function (PF) keys located on the front panel permit adjustment and testing of repeater sites. In addition, single priority scan is available when the unit is operating in simplex mode.

QT/DQT WITH DSP MULTI-DECODE

For QT/DQT groups sharing the same RF signal range, DSP processing allows up to 16 QT/DQT signal variations to be processed simultaneously via the multi-decode function. Two decode tables (main/sub) are available to facilitate the setup of channels to different multi-decode ranges.

COMPANDED AUDIO

A built-in compander contributes to improved audio when operating as a simplex base station. A wide/narrow setting is available for each channel.

FLASH MEMORY

Flash memory permits updates, advanced feature sets and system architectural changes to be made electronically without ever opening the unit. This means faster modifications for system operators and less downtime for users.

2-DIGIT NUMERIC LED DISPLAY

The 2-digit numeric LED on the front panel displays channel number and operational status information, such as an "unlocked" error.

LED INDICATORS

The LED indicator lights provide clear system status information at a glance, including transmit, receive, battery backup, and DC power. If the transmitter or receiver becomes unlocked, the LEDs flash for quick problem assessment.



WIDE/NARROW CHANNEL BANDWIDTH PER CHANNEL

The TKR-750/850 can handle both existing wide-band systems and emerging narrow band applications for extra flexibility and long-term viability. For VHF channels, compatibility is provided for a minimum frequency of 2.5kHz (US only).

WINDOWS® PROGRAMMING AND TUNING SOFTWARE

The repeater can be programmed from a Windows® compatible PC quickly and efficiently — without ever opening the case — using the optional FPU and programming interface cable. Among the radio parameters available for programming are:

- Squelch
- RX audio signal output (RA)
- RX detector signal output (RD)
- RX frequency
- RF output power
- Maximum deviation
- TX audio input (TA)
- Signaling deviation (TD)
- Signaling balance
- QT deviation
- DQT deviation
- Test tone deviation
- CW ID deviation
- Repeat gain
- TX frequency

Manual tuning is available for the following settings: RX helical resonator block bandwidth, MCF waveform, Quad detector coil, and MIC sensitivity.

6 PF KEYS & LOCAL SPEAKER

In addition to 6 programmable function keys (each equipped with an LED indicator), the front panel has a built-in speaker. This makes it easy to check on repeater site reception conditions. There is also a microphone terminal to allow audio transmission.

EMBEDDED MESSAGE WITH PASSWORD LOCK

The repeater's flash memory can store an electronic message — with password protection — containing owner identification, property ID numbers, user and department names, service records, etc. Additionally, the FPU can be used to display an electronic serial number. A unit can thus be electronically identified even if the external labels, marking or factory serial numbers have been removed.

EXTERNAL CONTROL I/O

The D-SUB25 connector on the rear panel provides a control I/O interface for external controllers to enable customization and integration with other features and capabilities.

BATTERY BACKUP SYSTEM

Several power-saving features, including a display-off function, help to reduce energy consumption. A built-in backup system supports automatic switching to a 12v battery* if the AC-based power supply* fails.

**Not supplied*

DURABLE DIE-CAST CHASSIS CONSTRUCTION

The die-cast aluminum chassis with integrated heat sink is the key to the TKR-750/850's durability, service level and reduced weight. The entire unit is sealed to provide long-term protection even in the most demanding operating conditions.



Options



KMC-30
Microphone



KMC-9C
Desktop Microphone

* Not all accessories may be available, please contact dealers for details.

Specifications

	TKR-750	TKR-850
GENERAL		
Frequency Range Type 1:	146 – 174 MHz	440 – 470 MHz
Number of Channels	16	
Channel Spacing Wide Narrow (PLL channel stepping)	25 kHz 12.5 kHz (5, 6.25 kHz)	25 kHz 12.5 kHz (5, 6.25 kHz)
Operating Voltage	13.2 V DC	
Current Drain Standby Standby (w/power save) Receive Transmit/Receive	0.8 A 0.3 A Operating mode; DC-IN:Backup, FAN:Temp, SAVE:On, DISP:Off 1.2 A Less than 13 A	
Duty Cycle	Receive: 100%, Transmit: 100%	
Frequency Stability	±0.0002% (-30° C – +60° C)	±0.00015% (-30° C – +60° C)
Operating Temperature Range	-30° C – +60° C	
Dimensions (W x H x D)	483 x 88 x 340 mm	
Weight (net)	9.7 kg	
Applicable Standard	ETS-300-086, 219	ETS-300-086, 219
RECEIVER (Measurements made per ETS 300 086)		
Antenna Impedance	50 Ω	
Sensitivity:	0.45 μV	
Adjacent Channel Selectivity 25 kHz 12.5 kHz	85 dB 77 dB	83 dB 75 dB
Intermodulation	72 dB	
Spurious & Image Rejection	90 dB	
Audio Output (Ext. Speaker)	4 W (at 4 Ω, less than 5% distortion)	
Audio Distortion (Ext. Speaker)	Less than 2.5% at 1000 Hz	
Band Spread Type 1:	3 MHz	5 MHz
TRANSMITTER (Measurements made per ETS 300 086)		
RF Power Output	50 W adjustable to 25 watts (100% duty at 25W)	40 W adjustable to 25 watts (100% duty at 25W)
Antenna Impedance	50 Ω	
Modulation Limiting	±5kHz at ±25kHz ±2.5kHz at ±12.5kHz	
Spurious Emission	-36dBm ±1 GHz -30dBm > 1GHz	
FM Noise (EIA) 25kHz 12.5kHz	50 dB 45 dB	
Microphone Impedance	600 Ω	
Modulation Distortion	Less than 3% at 1000 Hz	
Band Spread Type 1:	28 MHz	30 MHz

	TKR-750	TKR-850
REPEATER CONTROL (Measurements made per TIA/EIA-603)		
Signaling (simultaneously) Maximum Number of Tones	16	
QT Decoder/Encoder Tone frequency Decoder response time Squelch tail elimination time Encoder frequency error Sensitivity	67.0 – 210.7Hz (0.1Hz step) 250ms or less 140 to 200 ms ±0.3% or less SINAD 8dB or less	
DQT Decoder/Encoder DQT code Decoder response time Turn-off code transmission time Sensitivity	23 bits total: 3-digit octal number (0 – 7,12bits) with error correction (11bits) 250ms or less 140 to 200 ms SINAD 8dB or less	
Time-out Timer	Off to 30 min.	
Repeat Hold Time	Off to 10 sec.	
EXTERNAL CONTROL		
CWID Maximum modulation CW tone frequency Morse code speed Maximum character memory	Maximum deviation of 40% ±10% 400Hz to 2000Hz, (default 800Hz) 5 to 30 word per minutes, (default 20WPM) Up to 32 characters (include space)	
CW Message Maximum character Number of banks	Up to 32 characters per bank (include space) 8 banks	
Test Tone Maximum modulation Test tone frequency	Maximum deviation of 60% 300Hz to 3000Hz (default 1000Hz)	

Kenwood follows a policy of continuous advancement in development.
For this reason specifications may be changed without notice.



JQA-1205 091-A
ISO9001 Registered
Communications Equipment Division
Kenwood Corporation
ISO9001 certification

KENWOOD CORPORATION

14-6, 1-chome, Dogenzaka, Shibuya-ku, Tokyo 150-8501, Japan

KENWOOD ELECTRONICS UK LIMITED

Kenwood House, Dwight Road, Watford, Herts., WD18 9EB, United Kingdom

www.kenwood-electronics.co.uk

COMTKR750&850WEB1